



Description

The Paxton10 Reader Converter allows for an easy upgrade path between Net2 and Paxton10, enabling existing Net2 readers to be used with a Paxton10 system, and also adds support for third party clock and data readers. It is simple to install to either the Paxton10 Door Controller or the Paxton10 Video Door Controller. It is suitable for internal use only, with an operating temperature of 0°C - 45°C and comes complete with a 5 year warranty.



5 Year Guarantee

Features

- 5 year warranty
- Simple installation to either a Paxton10 Door Controller or Paxton10 Video Controller
- Adds support for third party clock & data readers
- Adds support of Paxton Net2 Readers, Proximity, Keypad & Keypad Proximity

Product Table
